

CZ500 Microphone Sensitivity Software Flash

This software flash will allow for a higher sensitivity level for the CZ500 microphone. Possible sensitivity levels are +6dB, +9dB and +12dB. Only one sensitivity level can be flashed at a time.

Procedure:

1. Download desired sensitivity level file.
2. Extract (un-zip) file to your desktop
3. Copy “*.mcs” file in to the root of a blank USB drive.
4. Turn on CZ500
5. Remove detachable control panel and press the reset switch.
6. Reinstall panel and select the Tuner source
7. Connect USB drive to port on CZ500
8. The display will indicate USB → File Read → Servo Upgrading.
***** Important: DO NOT REMOVE CONSTANT POWER, Turn OFF ACC or REMOVE USB DRIVE *****
9. After 20 to 30 seconds the CZ500 will reboot and default to tuner FM 87.9.
10. Remove USB
11. Insert a CD and press the center button on rotary dial and preset 6 to display version information.
12. Version number should be: VS-0057 for +6dB, VS-0058 for +9dB, VS-0059 for +12dB.
13. Repair phone and test microphone functionality.

WARNING:

Failure to follow these steps exactly as prescribed may result in permanent product failure. Removing constant power, turning off the ignition, removing the USB drive or pressing any buttons other than indicated during the upgrade **WILL RESULT** in product failure. Clarion holds no responsibility for damages (directly or consequential) due to not following or interrupting the upgrade process in any way.